

ANGLE SENSOR

"Return Spring System, Analog Output"

RCB 3100



GENERAL FEATURES

- Non-contact measurement with return spring system
- 12 bit resolution
- User-selectable angle values up to 120°
- 0-10 VDC, 4-20 mA or ratiometric output options
- Resistant to harsh environmental conditions and vibration
- IP54 protection class
- Long service life
- Compact design
- High accuracy

RCB 3100 series return spring angle sensors make non-contact measurement with magnetic principle. They have a measuring range up to 120°. The measured angular position is transmitted via analog interfaces such as 0.5-4.5V, 0-10V or 4-20 mA.

RCB 3100 series sensors with 12 bit resolution and high accuracy provides long and stable operation. Thanks to its compact structure, it provides quick and simple installation. Optionally, different analog output signals, measuring range (angle value) or cable length can be requested.

TECHNICAL SPECIFICATIONS				
*Measuring Range	Can be produced in the desired range up to 120 °			
Measuring Type	Magnetic, non-contact			
Linearity	±%0.5 FS			
Resolution	12 bit			
Repeatability	0.1°			
Response Frequency	250 Hz			
*Output Signal		Ratiometric	010VDC	420 mA
	Supply Voltage	5 VDC	1532 VDC	932 VDC
	Load	≥ 1KΩ	≥ 1KΩ	0250 Ω
Current Consumption	30 mA max.			
Reverse Polarity Protection	Yes, only supply			
Electrical Connection	3 x 14 mm ² shielded cable and superseal connector			
Max Operational Speed	120 RPM			
Protection Class	IP54			
Operating Temperature	-25°C +85°C			
Material	Body: Aluminum			
	Shaft: Stainless Steel			

Note: The specifications specified by (*) vary depending on the model selected. The detailed code table for product selection is shown on page 3.

DS-RCB.002 Rev No:1

MECHANICAL DIMENSIONS (in mm) Counter Clockwise (CCW) 4.50

SAMPLE APPLICATION FIELDS

- Robotic systems
- Auto parts
- Solar and photovoltaic systems

- Automated guided systems
- Crane and lifting technology
- Wind power plant














- (1) When the output signal is selected as 4-20 mA or 0-10V, the supply voltage must be PP and when the ratiometric is selected, the supply voltage must be TTL.
- (2) Optionally, different cable lengths can be requested.

Sample Code: RCB 3100-030-PP-V-CW-0,5M-8-S76

RCB 3100 series, 0-30° measuring range, PP supply, 0-10V output, Output signal direction is clockwise, 0.5 m cable, 8 mm shaft, superseal connector

فروشگاه کانون ابزار

Atek Elektronik Sensör Teknolojileri Sanayi ve Ticaret A.Ş.

تلفن: 00 39 39 66 201 موبايل: 3023 147 0912 www.ali5.ir



Gebze OSB, 800. Sokak, No:814 Gebze/KOCAELİ



Tel: +90 262 673 76 00



Fax: +90 262 673 76 08



